

負荷容量とバックアップ時間

※周囲温度+25℃時初期特性での計算値であり、保証値ではありません。周囲温度や経過年数により実際の値と異なる場合があります。

●常時商用方式 (SXU-Z シリーズ)

時間：(分)

型式	20W	50W	100W	200W	300W	400W	600W
SXU-ZA501	81	45	22	8	3	-	-
SXU-Z751	151	85	47	22	13	8	4 (525W)

●パワーマルチプロセッシング方式 (SMU シリーズ)

時間：(分)

型式	20W	50W	100W	200W	300W	400W	600W	800W	1000W	1200W	1400W	1600W	1800W	2000W	2400W	2600W	2800W	3000W	3300W	3500W
SMU-EA/HA751	152	81	42	19	12	8	5 (525W)	-	-	-	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA102	-	118	65	32	20	14	8	6 (700W)	-	-	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152	-	134	81	42	27	19	12	8	5.5	5 (1050W)	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152+SMB-12-S×1	-	-	-	176	114	82	50	35	26	25 (1050W)	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152+SMB-12-S×2	-	-	-	-	160	98	68	51	48 (1050W)	-	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA202	-	-	-	108	74	56	36	25	18	15	11	-	-	-	-	-	-	-	-	-
SMU-EA/HA202+SMB-23-S×1	-	-	-	-	165	108	79	58	48	40	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA202+SMB-23-S×2	-	-	-	-	-	189	137	100	80	67	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA302	-	-	146	93	67	51	34	24	18	14	11	9	7	6	5.5 (2100W)	-	-	-	-	-
SMU-EA/HA302+SMB33S×1	-	-	-	-	152	102	76	60	49	41	34	30	25	23.5 (2100W)	-	-	-	-	-	-
SMU-EA/HA302+SMB33S×2	-	-	-	-	-	178	132	104	85	71	61	53	47	42 (2100W)	-	-	-	-	-	-
SMU-EA/HA302+SMB33S×3	-	-	-	-	-	-	-	151	124	104	89	78	69	65 (2100W)	-	-	-	-	-	-
SMU-HA102-R	-	118	65	32	20	14	8	6 (700W)	-	-	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152-R	-	134	81	42	27	19	12	8	5.5	5 (1050W)	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152-R+SMB-12-R×1	-	-	-	176	114	82	50	35	26	25 (1050W)	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA152-R+SMB-12-R×2	-	-	-	-	160	98	68	51	48 (1050W)	-	-	-	-	-	-	-	-	-	-	-
SMU-EA/HA302-R	-	-	146	93	67	51	34	24	18	14	11	9	7	6	5.5 (2100W)	-	-	-	-	-
SMU-EA/HA302-R+SMB32R×2	-	-	-	-	-	127	94	74	60	51	43	37	33	31 (2100W)	-	-	-	-	-	-
SMU-EA/HA302-R+SMB32R×3	-	-	-	-	-	178	132	104	85	71	61	53	47	42 (2100W)	-	-	-	-	-	-
SMU-EA/HA302-R+SMB32R×5	-	-	-	-	-	-	-	168	137	115	99	86	76	72 (2100W)	-	-	-	-	-	-
SMU-HF152-R	-	143	73	38	26	18	11	8	5.4	5 (1050W)	-	-	-	-	-	-	-	-	-	-
SMU-HF152-R+SMB-HF14-R×1	-	-	-	-	140	85	58	46	44 (1050W)	-	-	-	-	-	-	-	-	-	-	-
SMU-HF152-R+SMB-HF14-R×2	-	-	-	-	265	180	130	100	92 (1050W)	-	-	-	-	-	-	-	-	-	-	-
SMU-HF302-R	-	-	-	92	61	44	29	20	15	12	10	8	7	5.4	5 (2100W)	-	-	-	-	-
SMU-HF302-R+SMB-HF32-R×1	-	-	-	-	170	123	90	70	55	43	36	30	26	24 (2100W)	-	-	-	-	-	-
SMU-HF302-R+SMB-HF32-R×2	-	-	-	-	-	147	116	95	79	67	58	51	48 (2100W)	-	-	-	-	-	-	-
SMU-HF302-R+SMB-HF32-R×3	-	-	-	-	-	-	-	148	125	107	91	79	73 (2100W)	-	-	-	-	-	-	-
SMU-HF502-R	-	-	-	132	99	63	46	36	30	25	21	18	16	12	11	10	9	7.5	7	7
SMU-HF502-R+SMB-HF52-R×1	-	-	-	-	148	110	88	71	60	51	45	40	33	30	27	25	21	20	20	20
SMU-HF502-R+SMB-HF52-R×2	-	-	-	-	-	138	115	97	83	73	64	52	47	43	40	35	33	33	33	33
SMU-HF502-R+SMB-HF52-R×3	-	-	-	-	-	163	140	120	105	94	77	71	65	60	53	49	49	49	49	49
SMU-HF502-R+SMB-HF52-R×4	-	-	-	-	-	170	148	131	117	95	87	80	73	64	60	53	49	49	49	49
SMU-HF502-R+SMB-HF52-R×5	-	-	-	-	-	164	146	129	119	109	99	90	79	72	64	57	50	43	36	30

●常時インバータ方式 (SRU シリーズ)

時間：(分)

型式	20W	50W	100W	200W	300W	400W	600W	800W	1000W	1200W
SRU751	-	93	48	22	12	8	5 (525W)	-	-	-
SRU102	-	170	68	33	20	13	7	5 (700W)	-	-
SRU102+SRB-102×1	-	-	-	155	95	65	40	31 (700W)	-	-
SRU102+SRB-102×2	-	-	-	-	177	124	76	60 (700W)	-	-
SRU152	-	-	105	48	31	21	13	8.8	5.8	5 (1050W)
SRU152+SRB-152-10M	-	-	-	82	53	39	23	16	11	10 (1050W)
SRU152+SRB-152×1	-	-	-	132	95	59	42	31	23 (1050W)	23 (1050W)
SRU152+SRB-152×2	-	-	-	-	110	78	62	53 (1050W)	53 (1050W)	53 (1050W)

●常時インバータ方式 (SAU シリーズ)

時間：(分)

型式	20W	50W	100W	200W	300W	400W	600W	800W	1000W	1200W	1400W	1600W	1800W	2000W	2400W	2600W	2800W	3000W	3300W	3500W	4000W	6000W	8000W	
SAU-A202	-	-	172	103	72	54	35	25	19	14	11	9	-	-	-	-	-	-	-	-	-	-	-	-
SAU-A202+SAB21	-	-	-	-	163	124	82	60	46	37	31	26	-	-	-	-	-	-	-	-	-	-	-	-
SAU-A202+SAB22	-	-	-	-	-	132	97	75	61	51	43	-	-	-	-	-	-	-	-	-	-	-	-	-
SAU-A302	-	-	-	141	103	80	54	40	31	25	21	17	14	12	9	-	-	-	-	-	-	-	-	-
SAU-A302+SAB31	-	-	-	-	-	124	92	73	60	50	43	37	33	26	-	-	-	-	-	-	-	-	-	-
SAU-A302+SAB32	-	-	-	-	-	-	149	118	97	81	70	61	54	43	-	-	-	-	-	-	-	-	-	-
SAU-A502	-	-	-	-	152	123	88	68	54	45	38	33	29	25	20	18	16	14	12	11	9	-	-	-
SAU-A502+SAB51	-	-	-	-	-	-	154	124	103	88	76	67	60	49	44	41	37	33	31	26	-	-	-	-
SAU-A502+SAB52	-	-	-	-	-	-	-	166	142	123	108	97	79	72	66	61	55	51	43	-	-	-	-	-
SAU752	-	-	-	-	-	118	92	71	65	55	47	41	35	29	26	24	22	19	18	15	10	-	-	-
SAU752+SAB-071	-	-	-	-	-	-	-	-	-	127	110	95	84	69	63	58	52	47	44	38	22	-	-	-
SAU103	-	-	-	-	-	-	-	123	105	92	81	72	64	52	47	43	39	35	33	28	17	12	-	-
SAU103+SAB-101	-	-	-	-	-	-	-	-	-	-	-	-	-	128	118	108	99	89	83	71	43	29	-	-